


**Note:**

1. An air space of not less than 150mm (6 inches) is required between transformer enclosures and between a transformer enclosure and any adjacent surface except floor.
2. Please ensure that aluminum mesh filter is installed behind each chevron panel.
3. Adequate ventilation is essential for the proper cooling of transformer. Those filters should be inspected for dust and cleaned to permit free circulation of air.

CSA Enclosure: E12-6  
 1. Type 12 (NEMA 12)  
 2. Ventilated  
 3. ASA 61 Grey  
 4. Floor mounting  
 5. Weight: 103.23 Lbs

UNLESS OTHERWISE SPECIFIED: DIMENSIONS ARE IN INCHES .XX = ± 0.05" .XXX = ± 0.030" .XXXX = ± 0.005" FRACTIONS = ± 1/16" ANGLES = ± 1°	NAME	DATE	<b>TITLE:</b> <b>STANDARD ENCLOSURE</b> <b>- NEMA 12 #6</b> <b>ASSEMBLY</b>	
	DRAWN	WW		
	APPROVED	VS	6/21/2019	<b>SIZE</b> <b>DWG. NO.</b> <b>REV</b> <b>A</b> E12-6 <b>3</b>
	MATERIAL	STEEL		
FINISH	ASA61 GREY		<b>SCALE: NTS</b> <b>WEIGHT: 103.23 LBS</b> <b>SHEET 1 OF 1</b>	



THIRD-ANGLE PROJECTION

